be quiet!

# be quiet! Pure Power 11 FM 550W

317L0500000093

Lab ID BQ55001797

Certification ID 251797

Test Result Report ID: 21PS1797A

Certificate Issue Date: Feb 23, 2021

Scheme: ETA-EMI PSU

115V




230V




115V




230V




Scheme: LAMBDA PSU



Aristeidis Bitziopoulos, Certification Body General Manager

# General Information

## Test Equipment

| | |
|---|---|
| Electronic Loads | Chroma 63601-5 x2<br>Chroma 63600-2<br>Chroma 63640-80-80 x10<br>Chroma 63610-80-20 |
| AC Sources | Chroma 6530, APM SP300VAC4000W-P, GW Instek ASR-3500 |
| Power Analyzers | Rohde & Schwarz HMC8015 & NPA701 |
| Oscilloscopes | Picoscope 4444, Siglent SDS2104X PLUS |
| Sound Analyzer | Bruel & Kjaer 2270 G4 |
| Microphone | Bruel & Kjaer Type 4955-A |
| Temperature Logger | Picoscope TC-08 |
| Tachometer | UNI-T UT372 |
| Multimeters | Keysight 34465A |
| EMI Analyzer | TekBox TBMR-110M-EU |
| Isolation Transformer | 4kVA |
| UPS | FSP Champ Tower 3kVA, CyberPower OLS3000E 3kVA |
| Testing Methodology | Cybenetics PSU Test Protocol |

## DUT Information(Non-accredited measurements)

| | |
|---|---|
| Product Identification Details | |
| Brand | be quiet! |
| Model | Pure Power 11 FM 550W |
| OEM/ODM | Channel Well Technology |
| Serial Number | 317L0500000093 |
| Product Specifications | |
| Manufacturer-Provided Information | |
| □□□□ (Vrms) | 100-240 |
| □□□□ (Arms) | 10-5 |
| □□□□ (Hz) | 50-60 |

| | |
|---|---|
| □□□□ (W) | 550 |
| Operating Temperature (Continuous Full Load) (°C) | |
| □□ | ATX12V |
| □□□□ | Fully Modular |
| Warranty | - |
| Cybenetics Measurements | |
| Dimensions (W x H x D) | |
| Weight | |
| □□ | 120mm Rifle Bearing Fan<br>(BQ QF2-12025-MS) |
| □□□□□ | ✗ |
| Cybenetics Testing Information | |
| Lab ID | BQ55001797 |
| Date of receipt | Feb 10, 2021 |
| Testing Date | Feb 23, 2021 |
| Report Issued Date | Feb 23, 2021 |
| Engineer Name | - |
| Authorized By the Laboratory Technical Manager | Aristeidis Bitziopoulos |
| Signature |  |

## □□□□ (Non-accredited measurements)

| □□□□ | | | | |
|---|---|---|---|---|
| □□ | □□□□ | □□□□□ | Gauge | In Cable Capacitors |
| ATX □□ 20+4 pin (550mm) | 1 | 1 | 16-18AWG | □ |
| 4+4 pin EPS 12V □□ (600mm) | 1 | 1 | 16AWG | □ |
| 6+2pin PCIe□□ (500mm) | 2 | 2 | 16AWG | □ |
| SATA□□ (500mm+150mm+150mm) | 1 | 3 | 18AWG | □ |
| SATA□□ (500mm+150mm+150mm+150mm) | 1 | 4 | 18AWG | □ |
| SATA□□ (500mm+150mm) / 4-pin Molex (+150mm+150mm) / FDD (+150mm) | 1 | 2 / 2 / 1 | 18-20AWG | □ |
| AC Power Cord (1400mm) - C13 coupler | 1 | 1 | 18AWG | - |

□□□□

| □ | | 3.3V | 5V | 12V(1) | 12V(2) | 5VSB | -12V |
|---|---|---|---|---|---|---|---|
| □□□□ | □□ | 20 | 20 | 28 | 24 | 3 | 0.3 |
| | □ | 120 | | 550 | | 15 | 3.6 |
| □□□□□ (W) | | 550 | | | | | |

## Parts Description

| | |
|---|---|
| General Data | - |
| Manufacturer (OEM) | CWT |
| PCB Type | Double Sided |
| Primary Side | - |
| Transient Filter | 4x Y caps, 2x X caps, 2x CM chokes, 1x MOV |
| Inrush Protection | NTC Thermistor SCK-075 (7Ohm) & Relay |
| Bridge Rectifier(s) | 1x  GBJ1506 (600V, 15A @ 100°C) |
| APFC MOSFETs | 1x Infineon IPA60R125P6 (650V, 19A @ 100°C, Rds(on): 0.125Ohm) |
| APFC Boost Diode | 1x ON Semiconductor FFSP0665A (650V, 6A @ 153°C) |
| Bulk Cap(s) | 2x Teapo (400V, 220uF & 270uF each or 490uF combined, 2,000h @ 85°C, LH) |
| Main Switchers | 2x ON Semiconductor FCPF190N60E (600V, 13.1A @ 100°C, Rds(on): 0.19Ohm) |
| No Load Consumption FET | 1x Sync Power SPN5003 (500V, 20mA @ 70°C, Rds(on): 250Ohm) |
| APFC Controller | Champion CM6500UNX |
| Resonant Controller | Champion CU6901VAC |
| Topology | Primary side: APFC, Half-Bridge & LLC converter<br>Secondary side: Synchronous Rectification & DC-DC converters |
| Secondary Side | - |
| +12V MOSFETs | 4x SG40N01Q (40V, 131A @ 100°C, Rds(on): 1.7mOhm) |
| 5V & 3.3V | DC-DC Converters: 2x UBIQ QM3054M6 (30V, 61A @ 100°C, Rds(on): 4.8mOhm) & 2x UBIQ QN3107M6N (30V, 70A @ 100°C, Rds(on): 2.6mOhm)<br>PWM Controller(s): uPI-Semi uP3861P |
| Change Over Switch | 1x Sync Power SPN3006 MOSFET (30V, 57A @ 100°C, Rds(on): 5.5mOhm) |
| Filtering Capacitors | Electrolytic: 4x Teapo (1-3,000h @ 105°C, SC), 4x Elite (2-5,000h @ 105°C, ED), 6x Elite (4-10,000h @ 105°C, EY), 1x Teapo (1-5,000h @ 105°C, SJ)<br>Polymer: 18x APAQ |
| Supervisor IC | Weltrend WT7527RT (OCP, OVP, UVP, SCP, PG) |

| | |
|---|---|
| Fan Model | be quiet! BQ QF2-12025-MS (120mm, 12V, 0.20A, Rifle Bearing Fan) |
| 5VSB Circuit | - |
| Rectifier | 1x Silan Microelectronics SVF4N65RDTR FET (650V, 2.5A @ 100°C, Rds(on): 2.7Ohm) & 1x PS1045L SBR (45V, 10A) |
| Standby PWM Controller | On-Bright OB5282 |

# Test Results

## Temperature & Compliance Info

| | |
|---|---|
| □□□□ (°C /°F) | 28-32 / 82.4-89.6 |
| □□ ErP Lot3/6□□ | ✓ |
| □□ (EU) No 617/2013□□ | ✓ |
| ALPM (Alternative Low Power Mode) compatible | ✓ |

## Performance Summary

### 115V

| | |
|---|---|
| Accredited | |
| □□□□ (>1450 load combinations) | 88.895% |
| Average Noise Output (>1450 Load Combinations) | 21.77dBA |
| PF□□□ (>1450 Load Combinations) | 0.990 |
| Efficiency With 10W (≤500W) or 2% (>500W) Load | 71.684% |
| □□□□□□ | 0.0392W |
| Non-Accredited | |
| 12V Ripple (Full Load) | 16.64mV |
| 5V Ripple (Full Load) | 9.95mV |
| 3.3V Ripple (Full Load) | 10.46mV |
| 5VSB Ripple (Full Load) | 10.82mV |
| 12V Load Regulation | 0.71% |
| 5V Load Regulation | 0.26% |
| 3.3V Load Regulation | 0.54% |
| 5VSB Load Regulation | 1.25% |

| | |
|---|---|
| Inrush Current | 22.780A |

## 230V


| | | |
|---|---|---|
| Accredited | | |
| □□□□ (>1450 load combinations) | | 90.771% |
| Average Noise Output (>1450 Load Combinations) | | 20.18dBA |
| PF□□□ (>1450 Load Combinations) | | 0.960 |
| Efficiency With 10W (≤500W) or 2% (>500W) Load | | - |
| □□□□□□ | | 0.0567W |
| Non-Accredited | | |
| 12V Ripple (Full Load) | | 17.97mV |
| 5V Ripple (Full Load) | | 9.54mV |
| 3.3V Ripple (Full Load) | | 10.90mV |
| 5VSB Ripple (Full Load) | | 11.17mV |
| 12V Load Regulation | | 0.71% |
| 5V Load Regulation | | 0.26% |
| 3.3V Load Regulation | | 0.51% |
| 5VSB Load Regulation | | 1.27% |
| Inrush Current | | 83.720A |
| □□□□ & PG□□ | | 19.70ms |
| AC Loss to PWR_OK Hold Up Time | | 15.90ms |
| PWR_OK Inactive to DC Loss Delay | | 3.80ms |
| PSU Timings: T1 (20% / 100%) | 52.0ms | 52.0ms |
| PSU Timings: T3 (20% / 100%) | 132.0ms | 132.0ms |
| OPP (22.06°C / 45.60°C) | 126.08% | 126.08% |

## □□□□ & PG□□


| | |
|---|---|
| Hold-Up Time (ms) | 19.7 |
| AC Loss to PWR_OK Hold Up Time (ms) | 15.9 |
| PWR_OK Inactive to DC Loss Delay (ms) | 3.8 |

## Graphs

### 115V





### 230V



## □□□□□□


### 115V




□□

This graph depicts the PSU`s efficiency throughout its entire operational range. For the generation of the efficiency and noise graphs we set our loaders to auto mode through our custom-made software before trying thousands of possible load combinations


## 230V




This graph depicts the PSU`s efficiency throughout its entire operational range. For the generation of the efficiency and noise graphs we set our loaders to auto mode through our custom-made software before trying thousands of possible load combinations

## □□□□□


### 115V




□□

The PSU`s noise in its entire operational range and under 30-32 °C ambient is depicted in this graph. The X axis represents the load on the +12V rail(s) while the Y axis is the load on the minor rails

## 230V




The PSU`s noise in its entire operational range and under 30-32 °C ambient is depicted in this graph. The X axis represents the load on the +12V rail(s) while the Y axis is the load on the minor rails

## Noise under high ambient temperature (indicative)

### 115V

| Load | Normal ambient<br>fan · noise · intake | High ambient<br>fan · noise · intake | Noise change |
|---|---|---|---|
| 10% | 510 RPM · <6.0 dB(A) · 40.2 °C | 510 RPM · <6.0 dB(A) · 40.2 °C | fan off in both |
| 20% | 5137 RPM · <6.0 dB(A) · 41.1 °C | 5137 RPM · <6.0 dB(A) · 41.1 °C | fan off in both |
| 50% | 994 RPM · 22.9 dB(A) · 42.7 °C | 994 RPM · 22.9 dB(A) · 42.7 °C | **+0.0 dB(A)** |
| 100% | 1700 RPM · 38.6 dB(A) · 45.7 °C | 1700 RPM · 38.6 dB(A) · 45.7 °C | **+0.0 dB(A)** |

### 230V


| Load | Normal ambient<br>fan · noise · intake | High ambient<br>fan · noise · intake | Noise change |
|---|---|---|---|
| 10% | 503 RPM · <6.0 dB(A) · 40.2 °C | 503 RPM · <6.0 dB(A) · 40.2 °C | fan off in both |
| 20% | 506 RPM · <6.0 dB(A) · 40.7 °C | 506 RPM · <6.0 dB(A) · 40.7 °C | fan off in both |
| 50% | 512 RPM · <6.0 dB(A) · 42.3 °C | 512 RPM · <6.0 dB(A) · 42.3 °C | fan off in both |
| 100% | 1719 RPM · 38.9 dB(A) · 44.8 °C | 1719 RPM · 38.9 dB(A) · 44.8 °C | **+0.0 dB(A)** |

### INFO

Fan speed, noise and the measured intake temperature at 10, 20, 50 and 100 % load, from the two load regulation tests: at normal ambient (about 30-32 °C) and at high ambient (about 40-47 °C). These are stabilized readings at fixed loads, not averages over the certification sweep, so they are indicative of how the fan behaves when it is hot. "<6.0" is the floor of our sound meter, with the fan stopped; with the fan stopped, the intake sensor can read higher than the chamber air.


*Informational. Not part of the ETA or LAMBDA rating.*

## Indicative Performance




The PSU`s efficiency under high ambient temperatures with 115V and 230V input. For this graph the results of the 10-110% load regulation table are used

**5Vsb□□□□**




□□

This graph depicts the efficiency levels of the 5VSB rail with 115V and 230V input

## □□□□ □□ 5Vsb □□ (ErP Lot3/6 & CEC)

### 115V

| □□ # | 5VSB | DC/AC (□ ) | □□ | PF/AC □□ |
|---|---|---|---|---|
| 1 | 0.045A | 0.227 | 70.062% | 0.037 |
| | 5.040V | 0.324 | | 115.15V |
| 2 | 0.090A | 0.453 | 75.000% | 0.069 |
| | 5.039V | 0.604 | | 115.16V |
| 3 | 0.550A | 2.768 | 79.931% | 0.289 |
| | 5.034V | 3.463 | | 115.15V |
| 4 | 1.000A | 5.026 | 79.337% | 0.386 |
| | 5.027V | 6.335 | | 115.16V |
| 5 | 1.500A | 7.528 | 79.309% | 0.442 |
| | 5.018V | 9.492 | | 115.16V |
| 6 | 2.999A | 14.985 | 78.014% | 0.502 |
| | 4.996V | 19.208 | | 115.16V |

### 230V

| □□ # | 5VSB | DC/AC (□ ) | □□ | PF/AC □□ |
|---|---|---|---|---|
| 1 | 0.045A | 0.227 | 63.231% | 0.012 |
| | 5.044V | 0.359 | | 230.31V |
| 2 | 0.090A | 0.454 | 70.497% | 0.022 |
| | 5.041V | 0.644 | | 230.32V |
| 3 | 0.550A | 2.768 | 78.192% | 0.114 |
| | 5.033V | 3.540 | | 230.31V |
| 4 | 1.000A | 5.027 | 78.979% | 0.188 |
| | 5.026V | 6.365 | | 230.31V |
| 5 | 1.500A | 7.529 | 79.403% | 0.250 |
| | 5.020V | 9.482 | | 230.31V |
| 6 | 3.000A | 14.986 | 79.853% | 0.358 |
| | 4.995V | 18.767 | | 230.32V |

## Supplementary Tests (For Reference)

### 10-110%□□□□

#### 115V

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□□ (dB[A]) | □□ (□□ /□□ ) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 2.766A | 1.982A | 1.994A | 0.995A | 54.959 | 85.050% | 510 | <6.0 | 40.22°C | 0.968 |
| | 12.058V | 5.047V | 3.311V | 5.026V | 64.620 | | | | 44.77°C | 115.17V |
| 2 | 6.517A | 2.972A | 2.992A | 1.195A | 110.035 | 88.264% | 5137 | <6.0 | 41.10°C | 0.988 |
| | 12.143V | 5.046V | 3.309V | 5.022V | 124.666 | | | | 46.68°C | 115.17V |
| 3 | 10.632A | 3.469A | 3.492A | 1.396A | 165.030 | 90.776% | 515 | <6.0 | 41.79°C | 0.992 |
| | 12.131V | 5.045V | 3.307V | 5.017V | 181.800 | | | | 47.88°C | 115.17V |
| 4 | 14.768A | 3.964A | 3.994A | 1.597A | 220.035 | 91.141% | 533 | <6.0 | 42.33°C | 0.994 |
| | 12.110V | 5.043V | 3.305V | 5.012V | 241.422 | | | | 49.23°C | 115.17V |
| 5 | 18.563A | 4.959A | 4.997A | 1.798A | 275.030 | 90.916% | 994 | 22.9 | 42.68°C | 0.995 |
| | 12.095V | 5.042V | 3.303V | 5.007V | 302.511 | | | | 50.60°C | 115.16V |
| 6 | 22.372A | 5.954A | 5.998A | 2.000A | 330.021 | 90.422% | 1271 | 29.5 | 43.35°C | 0.993 |
| | 12.078V | 5.040V | 3.301V | 5.002V | 364.979 | | | | 51.54°C | 115.17V |
| 7 | 26.193A | 6.948A | 7.000A | 2.201A | 385.078 | 89.936% | 1563 | 35.9 | 44.41°C | 0.994 |
| | 12.063V | 5.039V | 3.300V | 4.998V | 428.171 | | | | 53.18°C | 115.16V |
| 8 | 29.972A | 7.944A | 8.002A | 2.403A | 439.958 | 89.360% | 1702 | 38.6 | 44.57°C | 0.994 |
| | 12.063V | 5.037V | 3.298V | 4.994V | 492.341 | | | | 53.83°C | 115.15V |
| 9 | 34.147A | 8.438A | 8.490A | 2.403A | 494.402 | 89.012% | 1703 | 38.6 | 45.61°C | 0.995 |
| | 12.063V | 5.036V | 3.297V | 4.994V | 555.434 | | | | 55.32°C | 115.13V |
| 10 | 38.116A | 8.938A | 9.014A | 3.013A | 549.614 | 88.438% | 1700 | 38.6 | 45.65°C | 0.995 |
| | 12.066V | 5.035V | 3.295V | 4.979V | 621.467 | | | | 55.98°C | 115.13V |
| 11 | 42.694A | 8.940A | 9.016A | 3.013A | 604.838 | 87.930% | 1698 | 38.4 | 46.57°C | 0.996 |
| | 12.066V | 5.033V | 3.294V | 4.978V | 687.860 | | | | 57.33°C | 115.12V |
| CL1 | 0.114A | 14.002A | 13.998A | 0.000A | 118.189 | 82.908% | 1214 | 28.2 | 42.56°C | 0.990 |
| | 12.138V | 5.044V | 3.299V | 5.063V | 142.555 | | | | 50.46°C | 115.15V |

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| CL2 | 45.820A | 1.000A | 1.002A | 1.000A | 566.499 | 89.128% | 1699 | 38.4 | 45.12°C | 0.995 |
| | 12.072V | 5.038V | 3.299V | 5.016V | 635.602 | | | | 55.75°C | 115.13V |

The results above are not used in the certification process

## 230V

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□ (dB[A]) | □□ (□□ /□□ ) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 2.766A | 1.981A | 1.994A | 0.994A | 54.945 | 86.010% | 503 | <6.0 | 40.16°C | 0.794 |
| | 12.057V | 5.048V | 3.309V | 5.028V | 63.882 | | | | 45.01°C | 230.28V |
| 2 | 6.516A | 2.972A | 2.993A | 1.194A | 109.994 | 89.272% | 506 | <6.0 | 40.65°C | 0.917 |
| | 12.139V | 5.046V | 3.308V | 5.024V | 123.212 | | | | 46.18°C | 230.28V |
| 3 | 10.630A | 3.468A | 3.494A | 1.395A | 164.980 | 92.063% | 509 | <6.0 | 41.61°C | 0.952 |
| | 12.129V | 5.045V | 3.306V | 5.019V | 179.204 | | | | 47.61°C | 230.27V |
| 4 | 14.767A | 3.964A | 3.995A | 1.595A | 219.975 | 92.814% | 510 | <6.0 | 41.73°C | 0.968 |
| | 12.107V | 5.044V | 3.304V | 5.014V | 237.007 | | | | 48.53°C | 230.27V |
| 5 | 18.562A | 4.958A | 4.995A | 1.797A | 274.968 | 92.875% | 512 | <6.0 | 42.33°C | 0.976 |
| | 12.093V | 5.043V | 3.302V | 5.009V | 296.062 | | | | 50.09°C | 230.27V |
| 6 | 22.364A | 5.952A | 6.000A | 1.998A | 329.961 | 92.456% | 1333 | 31.6 | 42.75°C | 0.981 |
| | 12.080V | 5.041V | 3.300V | 5.005V | 356.885 | | | | 51.14°C | 230.28V |
| 7 | 26.176A | 6.947A | 7.008A | 2.200A | 385.034 | 92.098% | 1704 | 38.6 | 43.28°C | 0.984 |
| | 12.069V | 5.040V | 3.297V | 4.999V | 418.070 | | | | 52.24°C | 230.30V |
| 8 | 29.957A | 7.943A | 8.010A | 2.402A | 439.869 | 91.776% | 1696 | 38.4 | 43.85°C | 0.986 |
| | 12.066V | 5.038V | 3.295V | 4.995V | 479.287 | | | | 53.35°C | 230.30V |
| 9 | 34.143A | 8.437A | 8.498A | 2.403A | 494.383 | 91.512% | 1700 | 38.6 | 44.08°C | 0.988 |
| | 12.064V | 5.036V | 3.294V | 4.994V | 540.239 | | | | 54.18°C | 230.31V |
| 10 | 38.121A | 8.938A | 9.018A | 3.013A | 549.594 | 91.212% | 1719 | 38.9 | 44.75°C | 0.989 |
| | 12.064V | 5.035V | 3.293V | 4.979V | 602.543 | | | | 55.29°C | 230.31V |
| 11 | 42.680A | 8.940A | 9.023A | 3.014A | 604.829 | 90.922% | 1722 | 38.9 | 46.57°C | 0.990 |
| | 12.070V | 5.033V | 3.290V | 4.977V | 665.218 | | | | 57.35°C | 230.31V |
| CL1 | 0.116A | 14.000A | 13.997A | 0.000A | 118.144 | 83.978% | 1461 | 34.1 | 41.93°C | 0.933 |
| | 12.141V | 5.043V | 3.296V | 5.063V | 140.684 | | | | 50.29°C | 230.33V |

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| CL2 | 45.825A | 1.000A | 1.000A | 1.000A | 566.644 | 91.903% | 1714 | 38.8 | 44.60°C | 0.989 |
| | 12.074V | 5.038V | 3.298V | 5.016V | 616.565 | | | | 55.57°C | 230.32V |

The results above are not used in the certification process

## 20-80□□□□□

### 115V

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□ (dB[A]) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|
| 1 | 1.232A | 0.495A | 0.497A | 0.198A | 19.986 | 79.395% | 503 | <6.0 | 0.861 |
| | 12.047V | 5.048V | 3.313V | 5.042V | 25.173 | | | | 115.15V |
| 2 | 2.461A | 0.991A | 0.996A | 0.397A | 39.976 | 84.149% | 504 | <6.0 | 0.948 |
| | 12.057V | 5.048V | 3.313V | 5.039V | 47.506 | | | | 115.15V |
| 3 | 3.688A | 1.486A | 1.494A | 0.596A | 60.006 | 83.563% | 504 | <6.0 | 0.972 |
| | 12.082V | 5.047V | 3.312V | 5.034V | 71.809 | | | | 115.15V |
| 4 | 4.893A | 1.980A | 1.993A | 0.795A | 79.955 | 85.681% | 506 | <6.0 | 0.982 |
| | 12.132V | 5.047V | 3.312V | 5.030V | 93.317 | | | | 115.15V |

The results above are not used in the certification process

### 230V

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□ (dB[A]) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|
| 1 | 1.231A | 0.495A | 0.498A | 0.198A | 19.977 | 79.111% | 502 | <6.0 | 0.493 |
| | 12.047V | 5.048V | 3.310V | 5.043V | 25.252 | | | | 230.27V |
| 2 | 2.461A | 0.990A | 0.996A | 0.397A | 39.965 | 84.405% | 496 | <6.0 | 0.702 |
| | 12.055V | 5.048V | 3.311V | 5.040V | 47.349 | | | | 230.27V |
| 3 | 3.687A | 1.487A | 1.495A | 0.596A | 59.997 | 84.371% | 499 | <6.0 | 0.820 |
| | 12.080V | 5.048V | 3.311V | 5.036V | 71.111 | | | | 230.27V |
| 4 | 4.892A | 1.980A | 1.995A | 0.795A | 79.949 | 86.796% | 503 | <6.0 | 0.872 |
| | 12.133V | 5.047V | 3.309V | 5.032V | 92.111 | | | | 230.27V |

The results above are not used in the certification process

## □□□□

### 115V

| Test | 12V | 5V | 3.3V | 5VSB | Pass/Fail |
|---|---|---|---|---|---|
| 10% Load | 11.90mV | 5.40mV | 4.90mV | 6.10mV | Pass |
| 20% Load | 6.50mV | 5.00mV | 4.50mV | 5.90mV | Pass |
| 30% Load | 13.90mV | 5.80mV | 5.90mV | 6.60mV | Pass |
| 40% Load | 9.70mV | 5.40mV | 5.10mV | 6.90mV | Pass |
| 50% Load | 8.80mV | 5.90mV | 5.40mV | 7.20mV | Pass |
| 60% Load | 8.90mV | 6.40mV | 5.80mV | 7.80mV | Pass |
| 70% Load | 9.20mV | 8.90mV | 11.70mV | 10.20mV | Pass |
| 80% Load | 10.70mV | 9.00mV | 16.10mV | 10.50mV | Pass |
| 90% Load | 10.50mV | 8.10mV | 10.00mV | 9.80mV | Pass |
| 100% Load | 16.60mV | 10.00mV | 10.50mV | 10.80mV | Pass |
| 110% Load | 18.70mV | 10.10mV | 11.00mV | 11.30mV | Pass |
| Crossload1 | 8.30mV | 8.50mV | 9.60mV | 7.90mV | Pass |
| Crossload2 | 16.30mV | 7.90mV | 7.10mV | 9.90mV | Pass |

The results above are not used in the certification process

### 230V

| Test | 12V | 5V | 3.3V | 5VSB | Pass/Fail |
|---|---|---|---|---|---|
| 10% Load | 12.80mV | 5.40mV | 5.70mV | 7.20mV | Pass |
| 20% Load | 7.30mV | 6.00mV | 4.70mV | 6.90mV | Pass |
| 30% Load | 15.80mV | 5.90mV | 5.90mV | 7.80mV | Pass |
| 40% Load | 10.50mV | 5.90mV | 5.90mV | 7.90mV | Pass |
| 50% Load | 9.60mV | 6.40mV | 5.90mV | 8.10mV | Pass |
| 60% Load | 9.40mV | 6.80mV | 6.10mV | 8.70mV | Pass |
| 70% Load | 9.40mV | 8.60mV | 12.50mV | 10.70mV | Pass |
| 80% Load | 10.30mV | 9.80mV | 14.30mV | 11.30mV | Pass |

| Test | 12V | 5V | 3.3V | 5VSB | Pass/Fail |
|---|---|---|---|---|---|
| 90% Load | 11.20mV | 9.00mV | 10.50mV | 10.10mV | Pass |
| 100% Load | 18.00mV | 9.50mV | 10.90mV | 11.20mV | Pass |
| 110% Load | 19.20mV | 10.60mV | 10.90mV | 11.60mV | Pass |
| Crossload1 | 8.00mV | 8.70mV | 10.10mV | 8.10mV | Pass |
| Crossload2 | 17.60mV | 7.70mV | 7.40mV | 10.20mV | Pass |

The results above are not used in the certification process

## be quiet! Pure Power 11 FM 550W



Top side




Power specifications label