# Kolink Core 500W

CCW040120203481

Lab ID KL50001789

Certification ID 251789

Test Result Report ID: 21PS1789A

Certificate Issue Date: Feb 10, 2021

230V

Scheme: ETA-EMI PSU

230V




Scheme: LAMBDA PSU



Aristeidis Bitziopoulos, Certification Body General Manager

# General Information

## Test Equipment

| | |
|---|---|
| Electronic Loads | Chroma 63601-5 x2<br>Chroma 63600-2<br>Chroma 63640-80-80 x10<br>Chroma 63610-80-20 |
| AC Sources | Chroma 6530, APM SP300VAC4000W-P, GW Instek ASR-3500 |
| Power Analyzers | Rohde & Schwarz HMC8015 & NPA701 |
| Oscilloscopes | Picoscope 4444, Siglent SDS2104X PLUS |
| Sound Analyzer | Bruel & Kjaer 2270 G4 |
| Microphone | Bruel & Kjaer Type 4955-A |
| Temperature Logger | Picoscope TC-08 |
| Tachometer | UNI-T UT372 |
| Multimeters | Keysight 34465A |
| EMI Analyzer | TekBox TBMR-110M-EU |
| Isolation Transformer | 4kVA |
| UPS | FSP Champ Tower 3kVA, CyberPower OLS3000E 3kVA |
| Testing Methodology | Cybenetics PSU Test Protocol |

## DUT Information(Non-accredited measurements)

| | |
|---|---|
| Product Identification Details | |
| Brand | Kolink |
| Model | Core 500W |
| OEM/ODM | |
| Serial Number | CCW040120203481 |
| Product Specifications | |
| Manufacturer-Provided Information | |
| □□□□ (Vrms) | 200-240 |
| □□□□ (Arms) | 3 |
| □□□□ (Hz) | 50 |

| | |
|---|---|
| □□□□ (W) | 500 |
| Operating Temperature (Continuous Full Load) (°C) | |
| □□ | ATX12V |
| □□□□ | Fixed cables |
| Warranty | - |
| Cybenetics Measurements | |
| Dimensions (W x H x D) | |
| Weight | |
| □□ | 120mm Sleeve Bearing Fan<br>(WAM W 12025 HZ12SEMA) |
| □□□□□ | ✗ |
| Cybenetics Testing Information | |
| Lab ID | KL50001789 |
| Date of receipt | Jun 27, 2020 |
| Testing Date | Feb 4, 2021 |
| Report Issued Date | Feb 10, 2021 |
| Engineer Name | - |
| Authorized By the Laboratory Technical Manager | Aristeidis Bitziopoulos |
| Signature |  |

## □□□□□ (Non-accredited measurements)

| □□□□ | | | | |
|---|---|---|---|---|
| □□ | □□□□ | □□□□□□ | Gauge | In Cable Capacitors |
| ATX □□ 20+4 pin (530mm) | 1 | 1 | 18-20AWG | □ |
| 4+4 pin EPS 12V □□ (580mm) | 1 | 1 | 18AWG | □ |
| 6+2pin PCIe□□ (530mm) | 1 | 1 | 18AWG | □ |
| SATA□□ (430mm+150mm) / 4-pin Molex (+150mm) | 2 | 4 / 2 | 18AWG | □ |

| | | | | | | |
|---|---|---|---|---|---|---|
| | | 3.3V | 5V | 12V | 5VSB | -12V |
| | | 18 | 15 | 33 | 2.5 | 0.3 |
| | | 100 | | 396 | 12.5 | 3.6 |
| | (W) | 500 | | | | |

## Test Results

### Temperature & Compliance Info

| | |
|---|---|
| (°C /°F) | 28-32 / 82.4-89.6 |
| ErP Lot3/6 | ErP Lot 6 2010: ✓<br>ErP Lot 6 2013: ✓<br>ErP Lot 3 2014 & CEC: ✗ |
| (EU) No 617/2013 | ✗ |

### Performance Summary 230V


| | |
|---|---|
| Accredited | |
| (>1450 load combinations) | 81.920% |
| Average Noise Output (>1450 Load Combinations) | 26.56dBA |
| PF (>1450 Load Combinations) | 0.934 |
| Efficiency With 10W (≤500W) or 2% (>500W) Load | - |
| | 0.1537W |
| Non-Accredited | |
| 12V Ripple (Full Load) | 49.44mV |
| 5V Ripple (Full Load) | 39.18mV |
| 3.3V Ripple (Full Load) | 83.62mV |
| 5VSB Ripple (Full Load) | 32.14mV |
| 12V Load Regulation | 1.70% |
| 5V Load Regulation | 4.99% |
| 3.3V Load Regulation | 3.90% |

| | | |
|---|---|---|
| 5VSB Load Regulation | | 5.33% |
| Inrush Current | | 89.260A |
| □□□□ & PG□□ | | 8.70ms |
| AC Loss to PWR_OK Hold Up Time | | 15.80ms |
| PWR_OK Inactive to DC Loss Delay | | -7.10ms |
| PSU Timings: T1 (20% / 100%) | 60.0ms | 56.0ms |
| PSU Timings: T3 (20% / 100%) | 270.0ms | 286.0ms |
| OPP (25.80°C / 0.00°C) | 104.36% | - |


## □□□□ & PG□□

| | |
|---|---|
| Hold-Up Time (ms) | 8.7 |
| AC Loss to PWR_OK Hold Up Time (ms) | 15.8 |
| PWR_OK Inactive to DC Loss Delay (ms) | -7.1 |

## Graphs 230V


Power - CCW040120203481 - 02/02/2021 - 13:12
Power(W)
0.158
0.157
0.156
0.155
0.154
0.153
0.152
0.151
0
100
200
300
400
500
600
700
800
900
1000
Seconds (s)


## 230V




□□

This graph depicts the PSU`s efficiency throughout its entire operational range. For the generation of the efficiency and noise graphs we set our loaders to auto mode through our custom-made software before trying thousands of possible load combinations


### 230V




□□


The PSU`s noise in its entire operational range and under 30-32 °C ambient is depicted in this graph. The X axis represents the load on the +12V rail(s) while the Y axis is the load on the minor rails

## Indicative Performance




The PSU`s efficiency under high ambient temperatures with 115V and 230V input. For this graph the results of the 10-110% load regulation table are used

**5Vsb□□□□**




□□

This graph depicts the efficiency levels of the 5VSB rail with 115V and 230V input

**□□□□ □□ 5Vsb □□ (ErP Lot3/6 & CEC) 230V**

| □□ # | 5VSB | DC/AC (□ ) | □□ | PF/AC □□ |
|---|---|---|---|---|
| 1 | 0.045A | 0.231 | 48.632% | 0.014 |
| | 5.147V | 0.475 | | 230.30V |

| | | | | |
|---|---|---|---|---|
| 2 | 0.090A | 0.463 | 58.166% | 0.024 |
| | 5.144V | 0.796 | | 230.31V |
| 3 | 0.550A | 2.817 | 71.443% | 0.110 |
| | 5.122V | 3.943 | | 230.30V |
| 4 | 1.000A | 5.095 | 73.638% | 0.177 |
| | 5.095V | 6.919 | | 230.31V |
| 5 | 1.500A | 7.607 | 74.258% | 0.233 |
| | 5.072V | 10.244 | | 230.31V |
| 6 | 2.499A | 12.554 | 74.447% | 0.305 |
| | 5.023V | 16.863 | | 230.31V |

## Supplementary Tests (For Reference)

**10-110%□□□□ 230V**

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□ (dB[A]) | □□ (□□ /□□ ) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 1.471A | 1.977A | 1.979A | 0.984A | 39.986 | 75.801% | 939 | 21.7 | 30.12°C | 0.579 |
| | 12.503V | 5.059V | 3.333V | 5.078V | 52.751 | | | | 33.11°C | 230.25V |
| 2 | 3.936A | 2.979A | 2.981A | 1.187A | 80.009 | 82.109% | 939 | 21.7 | 30.77°C | 0.831 |
| | 12.478V | 5.037V | 3.319V | 5.052V | 97.442 | | | | 34.19°C | 230.25V |
| 3 | 6.750A | 3.476A | 3.491A | 1.392A | 119.946 | 84.181% | 940 | 21.7 | 31.26°C | 0.889 |
| | 12.431V | 5.033V | 3.307V | 5.027V | 142.485 | | | | 35.93°C | 230.26V |
| 4 | 9.591A | 3.977A | 4.007A | 1.599A | 159.979 | 84.662% | 951 | 21.3 | 31.58°C | 0.929 |
| | 12.385V | 5.028V | 3.294V | 5.003V | 188.961 | | | | 36.71°C | 230.26V |
| 5 | 12.087A | 5.000A | 5.032A | 1.809A | 200.003 | 84.350% | 964 | 21.2 | 32.22°C | 0.948 |
| | 12.368V | 5.001V | 3.280V | 4.976V | 237.110 | | | | 37.84°C | 230.28V |
| 6 | 14.580A | 6.038A | 6.064A | 2.000A | 239.848 | 83.750% | 1298 | 28.3 | 32.70°C | 0.958 |
| | 12.356V | 4.969V | 3.265V | 4.948V | 286.387 | | | | 38.83°C | 230.28V |
| 7 | 17.081A | 7.097A | 7.115A | 2.236A | 280.017 | 83.024% | 1441 | 31.0 | 33.39°C | 0.964 |
| | 12.347V | 4.933V | 3.248V | 4.919V | 337.272 | | | | 40.25°C | 230.29V |
| 8 | 19.580A | 8.002A | 8.163A | 2.452A | 319.202 | 82.310% | 1512 | 32.4 | 33.93°C | 0.967 |
| | 12.339V | 4.902V | 3.232V | 4.892V | 387.805 | | | | 41.57°C | 230.29V |

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| 9 | 22.525A | 8.712A | 8.696A | 2.461A | 359.918 | 81.654% | 1571 | 33.3 | 34.62°C | 0.970 |
| | 12.317V | 4.878V | 3.218V | 4.875V | 440.786 | | | | 42.81°C | 230.30V |
| 10 | 25.449A | 9.264A | 9.265A | 2.577A | 399.985 | 80.812% | 1734 | 36.8 | 35.09°C | 0.973 |
| | 12.291V | 4.858V | 3.204V | 4.851V | 494.957 | | | | 44.28°C | 230.31V |
| 11 | 28.814A | 9.266A | 9.302A | 2.586A | 439.881 | 79.873% | 1811 | 37.3 | 35.78°C | 0.975 |
| | 12.240V | 4.856V | 3.193V | 4.834V | 550.725 | | | | 45.54°C | 230.31V |
| CL1 | 0.000A | 00.000A | 00.000A | 00.000A | 0000.00 | 00.000% | 0 | 0 | 00.0°C | 0.000 |
| | 00.000V | 00.000V | 00.000V | 00.000V | 0000.00 | | | | 00.0°C | 000.0V |
| CL2 | 33.004A | 1.001A | 1.001A | 1.000A | 405.324 | 82.097% | 1494 | 32.0 | 32.14°C | 0.973 |
| | 11.875V | 5.188V | 3.243V | 4.962V | 493.714 | | | | 37.53°C | 230.30V |

The results above are not used in the certification process

### 20-80□□□□ 230V

| □□ # | 12V | 5V | 3.3V | 5VSB | DC/AC (□ ) | □□ | □□□□ (RPM) | □□□□□□□ (dB[A]) | PF/AC □□ |
|---|---|---|---|---|---|---|---|---|---|
| 1 | 1.191A | 0.488A | 0.493A | 0.195A | 19.974 | 69.705% | 906 | 19.4 | 0.404 |
| | 12.447V | 5.122V | 3.347V | 5.131V | 28.655 | | | | 230.21V |
| 2 | 2.384A | 0.978A | 0.989A | 0.391A | 39.964 | 77.916% | 913 | 19.3 | 0.570 |
| | 12.445V | 5.105V | 3.340V | 5.114V | 51.291 | | | | 230.22V |
| 3 | 3.582A | 1.474A | 1.483A | 0.589A | 59.996 | 81.577% | 921 | 18.7 | 0.708 |
| | 12.437V | 5.091V | 3.332V | 5.096V | 73.545 | | | | 230.23V |
| 4 | 4.776A | 1.969A | 1.984A | 0.788A | 79.948 | 83.326% | 926 | 18.9 | 0.825 |
| | 12.427V | 5.079V | 3.324V | 5.077V | 95.946 | | | | 230.24V |

The results above are not used in the certification process

### □□□□ 230V

| Test | 12V | 5V | 3.3V | 5VSB | Pass/Fail |
|---|---|---|---|---|---|
| 10% Load | 11.80mV | 10.60mV | 28.50mV | 7.50mV | Pass |
| 20% Load | 16.50mV | 16.50mV | 38.10mV | 13.00mV | Pass |
| 30% Load | 14.20mV | 14.60mV | 34.60mV | 12.20mV | Pass |
| 40% Load | 16.00mV | 16.50mV | 43.20mV | 14.30mV | Pass |


| Test | 12V | 5V | 3.3V | 5VSB | Pass/Fail |
|---|---|---|---|---|---|
| 50% Load | 17.00mV | 18.00mV | 43.40mV | 15.40mV | Pass |
| 60% Load | 26.40mV | 24.40mV | 46.60mV | 24.30mV | Pass |
| 70% Load | 31.10mV | 27.40mV | 62.00mV | 27.60mV | Fail |
| 80% Load | 38.40mV | 30.70mV | 74.20mV | 28.70mV | Fail |
| 90% Load | 41.60mV | 35.30mV | 76.40mV | 31.10mV | Fail |
| 100% Load | 49.40mV | 39.20mV | 83.60mV | 32.10mV | Fail |
| 110% Load | 57.40mV | 42.50mV | 83.00mV | 33.40mV | Fail |
| Crossload1 | 0.00mV | 0.00mV | 0.00mV | 0.00mV | Pass |
| Crossload2 | 37.50mV | 30.00mV | 37.10mV | 12.30mV | Pass |

The results above are not used in the certification process

## Kolink Core 500W



Top side




Power specifications label

Cybenetics
Cybenetics
ETA LAMBDA SAFE
DELTA PHI

CYBENETICS LTD Syrou 6, Latsia, 2231, Nicosia Cyprus
www.cybenetics.com - info@cybenetics.com